

Universal Power Supply (300V)

Cat. No. BT407

INTRODUCTION.....	3
TECHNICAL SPECIFICATIONS.....	3
CHARACTERISTIC FEATURES.....	3
SETUP AND OPERATION.....	3
ERROR ALARM.....	4
WARNING.....	5
IMPORTANT	5
ENVIRONMENTAL CONDITIONS.....	5
AVOIDING ELECTRICAL SHOCK.....	6
AVOIDING DAMAGE TO THE INSTRUMENT	6
EQUIPMENT OPERATION	7
WARRANTY	7
TECHNICAL SUPPORT	7

INTRODUCTION

The Universal Power supply (300V) has the following Technical specifications and Characteristic features:

Technical Specifications

- Type of Output: Constant-Voltage, Current or Power
- Increment: 1V, 1mA, 1W
- Timer Range: 1min-99hr:59min
- Display: LCD display with backlight
- Output jacks: Four sets of output jacks

Characteristic features

- Molding shell, touch keys, dual core microprocessor intelligent control;
- Indicate the preset value and the actual output value at the same time;
- It can store 10 electrophoresis methods;
- With automatic memory function;
- With standard, timing operation function;
- With constant voltage, constant current, constant power, incorrect operation, fault intelligent prompt functions;
- Automatic detection of no-load, over-load, short circuit, rapid resistance change, ground leak and system overheating.

SETUP AND OPERATION

1. Turn on the power switch, enter into Setting State.

EDIT [0]	
U = 100V	0v
I = 500mA	0mA
P = 300W	0w

2. The cursor will flash at "U=□□□V". Set the value of constant voltage by pressing "▲" or "▼" button.
3. The cursor will flash at "I = □□□mA" when press "ENT" button. Set the value of constant current by pressing "▲" or "▼" button
4. The cursor will flash at "P = □□□W" when press "ENT" button. Set the value of constant power by pressing "▲" or "▼" button. The range of power can be set from 1 to 300W. The cursor will return and flash at "U = □□□V" when you press "ENT" button. Set the value of constant voltage again by pressing "▲" or "▼" button.

5. Power supply in Setting State now. Press “RUN/STOP” button, it will enter into Operating State.

EDIT [0]	RUN! 00:01
U = 100V	▶ 100v
I = 500mA	350mA
P = 300W	35w

6. Power supply in Operating State now. Press “RUN/STOP” button, it will stop output and return to Setting State.

7. In Setting State, continue to press “EDIT” button, it will enter into Editing State and display:
 “SAVE [□]” → “LOAD [□]” → “T= □□:□□” → “QUIT” → “SAVE [□]” ...

EDIT [0]	
U = 100V	0v
I = 500mA	0mA
P = 300W	0w

8. At “SAVE □”, press “▲” or “▼” button to select number of memory program. The range of number is from 1 to 9. Then press “ENT” button to save current method into this program.
9. At “LOAD [□]”, press “▲” or “▼” button to select number that needed. The range of number is from 1 to 9. Then press “ENT” button to load the current method from program.
10. At “T= □□:□□”, press “▲” or “▼” button to set operating time.
11. The range of timer is from 1min to 99hs and 59mins. Then press “ENT” button to save it.

EDIT [0]	
U = 100V	0v
I = 500mA	0mA
P = 300W	0w

12. At “QUIT”, press “ENT” button to quit Editing state, and return to Setting State.

ERROR ALARM

1. When the power supply run with Over-load, it will stop automatically and alarm with buzzer, then display “ERROR 1!”. Turn off the switch immediately.
2. When the power supply run with No-load, It will stop automatically and alarm with buzzer, then display “ERROR 2!”. Turn off the switch immediately.

WARNING



Electrophoresis power supplies use high output voltages that are electrically isolated from earth ground through a protective impedance to minimize the risk of electrical shock to the user. The following guidelines should be observed and followed when using a power supply.



Electrophoresis power supplies have passed test for operation at temperatures between 0° and 40°C, with relative humidity between 0 and 95% non-condensing. Operating the power supply outside these conditions is not recommended by our company and will void the warranty.

1. To ensure adequate cooling of the power supply, be sure that there is at least 6 cm clearance around the power supply. Do not block the fan vents at the rear of the unit.
2. Always connect the power supply to a 3-prong, grounded AC outlet, using the 3-prong AC power cord provided with the power supply.
3. Do not operate the power supply in extreme humidity (>95%) or where condensation can short the internal electrical circuits of the power supply.
4. When taking the power supply into a cold room, the unit can be operated immediately. However, when removing the power supply from the cold room, let the unit equilibrate to room temperature for a minimum of 2 hours before using it.
5. Never connect a high voltage output lead to earth ground. This defeats the floating electrical isolation of the power supply and exposes the user to potentially lethal high voltages.

IMPORTANT

This instrument is intended for laboratory use only. This product conforms to the class A standards for Electromagnetic Emissions, intended for laboratory equipment applications. It is possible that emissions from this product may interfere with some sensitive appliances when placed nearby or on the same circuit as those appliances. The user should be aware of this potential and take appropriate measures to avoid interference.

ENVIRONMENTAL CONDITIONS

Ensure the instrument is installed and operated strictly under the following conditions:

1. Indoor use only
2. ≤95% RH
3. 75-106 kPa
4. Altitude must not exceed 2000 meters
5. 4-40°C operating temperature
6. Pollution degree: 2
7. Mains supply voltage fluctuations up to ±10% of the normal voltage

AVOIDING ELECTRICAL SHOCK

Follow the guidelines below to ensure safe operation of the unit.

The Basic Power Supply has been designed to utilize shielded wires thus minimizing any potential shock hazard to the user. BT Lab Systems recommends against the use of unshielded wires.

To avoid electrical shock:

1. In the event of solution spilling on the instrument, it must be dried out for at least 2 hours and restored to NORMAL CONDITION before each operation.
2. Never connect or disconnect wires loading from the power jacks when the red indicator light of power switch is on.
3. WAIT at least 5 seconds after stopping a run before handling output leads or any connected apparatus.
4. ALWAYS make sure that your hands, work area, and instruments are **clean** and **dry** before making any connections or operating the power supply.
5. ONLY connect the power cord to a properly grounded AC outlet.

AVOIDING DAMAGE TO THE INSTRUMENT

1. Do not attempt to operate the device if damage is suspected.
2. Protect this unit from physical damage, corrosive agents and extreme temperatures (direct sunlight, etc.).
3. For proper ventilation and safety concerns, keep at least 10 cm of space behind the instrument, and at least 6 cm of space on each side.
4. Use high level of precaution against the damages on the unit.
5. Do not operate the unit out of environmental conditions addressed above.
6. Do not operate the power supplies in high humidity environments (> 95%), or where condensation may occur.
7. To avoid condensation after operating the power supply in a cold room, wrap the unit in a plastic bag and allow at least 2 hours for the unit to equilibrate to room temperature before removing the bag and operating the unit.
8. Prior to applying any cleaning or decontamination methods other than manufacturer's recommendation, users should check with the manufacturer's instruction to see if the proposed method will damage the equipment.

EQUIPMENT OPERATION

Follow the guidelines below to ensure safe operation of the unit:

1. NEVER access dangerous chemicals or other materials to prevent possible hazard of explosion and damage.
2. Do not operate the unit without lids or covers to prevent possible hazards.
3. A temporary conductivity caused by condensation might occur even though this series is rated Pollution Degree 2 in accordance with IEC 664.

WARRANTY

BT Lab Systems warrants apparatus of its manufacture against defects in materials and workmanship, under normal service, for ***one year from the shipping date to purchaser***. This warranty excludes damages resulting from shipping, misuse, carelessness, or neglect. BT Lab Systems's liability under the warranty is limited to the receipt of reasonable proof by the customer that the defect is embraced within the terms of the warranty. All claims made under this warranty must be presented to BT Lab Systems within one year following the date of delivery of the product to the customer.

TECHNICAL SUPPORT

BT Lab Systems offers technical support for all of its products. If you have any questions about the product's use or, operation, please contact BT Lab Systems at the following info.

E-Mail: info@BTLabSystems.com